

# GuangDong FuDianKang Power Co., Ltd. ShenZhen FuDianKang Diesel Gensets Co., Ltd.

Tel: 86-13710087995

Web: www.fdkenergy.com

Email: info@fdkenergy.com

# **DATA SHEET**

DIESEL GENERATOR 158KW

MODEL#FDK-P198/H1

50HZ/1500RPM

PERKINS MODEL:1106A-70TAG3



#### **General Features:**

- All qualified generator sets are subjected to a comprehensive performance test which includes 50% load, 70% load, 100% load, 110% load and to check, verify that all control systems, alarm and shut-down protection.
- Equipped with battery charger and 24V high performance maintenance-free lead-acid starting batteries and connecting
- Stainless galvanized zinc plates with strong corrosion-proof.
- Vibration isolators between the engine/alternator and base frame.
- Equipped with industrial silencer and flexible exhaust hose.
- Designed to comply with ISO8528/GB2820.
- Powered by Perkins engine and coupled with Stamford alternator.
- Water jacket preheater, oil heater and double air cleaner, etc. are available.

#### **FDK Diesel Generator Set Data**

Genset Model	FDK-P198/H1
Prime Power	144KW/180KVA
Standby Power	158KW/198KVA
Output Frequency / Rated speed	50Hz/1500rpm
Rated Voltage	230V/400V

Engine Make	Perkins CHINA
Engine Model	1106A-70TAG3
Alternator model	Stamford UCI274G
Control System	DSE7320
Phase	Three

- (1) **Prime power**: The rating is available for an unlimited of annual operating hours in variable load applications, in accordance with ISO8528-1.A 10% overload is available for a period of 1 hour within 12-hour period of operation, in accordance with ISO 3046-1.
- (2) **Standby power**: The rating is applicable for supplying emergency power in variable load applications for up to 200 hours per year in accordance with ISO8528-1. Overload is not allowed.
- (3) Rated voltage: available with customer requirement.

#### Engine Specifications (DETAILED in APPENDIX)

Engine Model	1106A-70TAG3
Engine Manufacturer	Perkins CHINA
Cylinder quantity	6
Cylinder Arrangement	In-line
Cycle	4
Aspiration	Turbo charged

Bore x Stroke (mm x mm)	105×135
Displacement	7.01L
Compression Ratio	16:1
Prime power / Speed (KW/RPM)	144kw/1500
Standby power/ Speed (KW/RPM)	160kw/1500
Governor type	N.A.





# GuangDong FuDianKang Power Co., Ltd. ShenZhen FuDianKang Diesel Gensets Co., Ltd.

Tel: 86-13710087995

		Web: www.fdkenergy.com En	nail: info@fdkenergy.com
Piston Speed	N.A.	Fuel Consumption at 100% load (L/HOUR)	N.A.
ElectropaK net engine power	N.A.	Starter motor	N.A.
Total Lubrication System Capacity (L)	16.5	Alternator	N.A.
Total Coolant Capacity (L)	21	Minimum cranking speed.	N.A.

#### **Alternator Specifications**

Alternator model	UCI274G	Number of phases	3
Alternator manufacturer	STAMFORD	Rated voltage	400V (Available with
Exciter type	Single bearing, Brushless,		custom requirements)
	Self-excited	Power factor	0.8
Rated output prime power	180KVA	Voltage regulation NL-FL	≤±1%
Rated speed	1500 rpm	Insulation grade	Н
Rated frequency	50Hz	Protection grade	IP23

Alternator option: Leroy Somer, MECC, Marathon, Engga, Faraday

### Control System DSE7320 (DETAILED in INSTRUCTION)

DSE7320 is an advanced control module based on micro-processor, containing all necessary functions for protection of the genset and the breaker control. It can monitor the mains supply, breaker control and automatically start the engine when the mains are abnormal. Accurately measure various operational parameters and display all values and alarms information on the LCD. In addition, the control module can automatically shut down the engine and indicate the engine failure.

#### **FEATURES**

- Microprocessor control, with high stability and credibility.
- Monitoring and measuring operational parameters of the mains supply and genset.
- Indicating operation status, fault conditions, all parameters and alarms.
- Multiple protections; multiple parameters display, like pressure, temp. etc.
- Manual, automatic and remote work mode selectable.
- Real time clock for time and date display, overall runtime display, 250 log entries.
- Overall power output display.
- Integral speed/frequency detecting, telling status of start, rated operation, overspeed etc.
- Communication with PC via RS485 OR RS232 interface, using MODBUS protocol.

#### Soundproof Enclosure Specification

FDK silent generator is designed by professional acoustic engineers based on years of experience. Now we can make the noise of the generator less than 80-85dB(A) at 1m, or 70-75dB(A) at 7m, 60-65dB(A) at 15m.

## **FEATURES**

- Multi-way air intake and exhaust guarantee the power performance of the generator.
- Large-scale impedance combined type silencer effectively reduces noise of the generator.
- Internal high performance rubber damper and flexible materials reduce vibration.
- Base mounted fuel tank supports the generator running for 8 hours.

#### **Optional**





# GuangDong FuDianKang Power Co., Ltd. ShenZhen FuDianKang Diesel Gensets Co., Ltd.

Tel: 86-13710087995

Web: www.fdkenergy.com Email: info@fdkenergy.com Low environment Temp Generator set Alternator **ATS** Stamford Water heater CHINT Open generator set Oil heater **SCHNEIDER** Silent generator set Marathon Trailer generator set MeccAlte Battery heater ABB MCCB circuit breaker Leroy Somer Farady Engga Fuel system Control system Voltage Synchronized system 12hrs base tank AMF function 415/240V **CHINT Cabinet** SCHNEIDER Cabinet 24hrs base tank ATS control cabinet 400/230V Dual wall base fuel tank DSE7320 380/220V DSE8610 Module Outside fuel tank DSE7510 220/127V **COMAQ Module DEIF Module GU620A** 200/115V 

# **Dimension & Weight** Open

Overall Size:	2200×800×1313
L×W×H (mm)	
Weight (kg)	1300

## Soundproof Version

Overall Size: L×W×H (mm)	3000X1250X1800
Weight (kg)	2300

#### **Sales Promises**

- FDK provides a full line of brand new and high-quality products. Each and every unit is strictly factory tested before
- Quality warranty is according to our standard conditions: 12 months from BL date or 1000 running hours, whichever comes
- Service and parts are available from FDK or distributors in your location.

FDK guarantee use BRAND NEW & GENUINE MACHINE.

